

Automated Test Equipment (ATE) for EV Battery Management Systems (BMS): Challenges and Solutions

Sandeep D'Souza
Elevate Semiconductor



Suwon • October 29, 2024



Overview

- Battery pack and Battery Management Systems (BMS): Critical component of EV
- BMS and BMS-ATE: Key functions and challenges
- Proposed BMS-ATE Solution
 - System architecture and modes of operation
 - Parametric Measurement Unit (PMU) based architecture
 - PMU measured results
- Future trends
- Conclusion




Automated Test Equipment (ATE) for EV Battery Management Systems (BMS): Challenges and Solutions



EV Battery Pack: The New “Fuel Tank”

- Exponential growth in EVs driven by consumer adoption and government mandates
- Battery pack critical to EV safety, reliability and range
 - Multiple electric cars, trucks, tuk tuk and motorcycles on the market!
- Largest growth area is China
 - Motivates discussion at TestConX Korea




Automated Test Equipment (ATE) for EV Battery Management Systems (BMS): Challenges and Solutions



EV Battery Pack System Architecture

- EV battery-pack ~ 400V to 800V: Series connection of ~ 16 battery modules
- Each Battery module : (16 to 24 cells in series) X (70 to 100 cells in parallel)
- Each battery module has a dedicated BMS IC



**Focus of this talk

Example EV
Battery Systems
Tesla Model S




BYD Blade



Rivian R1T





Overview

- Battery pack and Battery Management Systems (BMS): Critical component of EV
- BMS and BMS-ATE: Key functions and challenges
- Proposed BMS-ATE Solution
 - System architecture and modes of operation
 - Parametric Measurement Unit (PMU) based architecture
 - PMU measured results
- Future trends
- Conclusion




Automated Test Equipment (ATE) for EV Battery Management Systems (BMS): Challenges and Solutions



BMS & BMS-ATE requirements for accurate cell-voltage measurement

- EV battery State-of-Charge (SoC) needs measurement of each cell-voltage
- EV battery cells have very flat discharge curves
 - BMS : Need accurate Analog-to-Digital Converters (ADCs) for cell-voltage measurement
 - ~100s microVolt precision needed to accurately calculate EV range
 - BMS-ATE : Automated-Test Equipment (ATE) needs accurate Digital-to-Analog Converters (DACs) to generate stimuli outputs for test of BMS ADC capabilities
 - ❖ BMS-ATE needs low-noise, high-linearity DAC and analog-front end (AFE)






Parameter	BMS IC		
	ADI	TI	ST
Cell Voltage Measurement	ADBMS6830B	BQ79616	L9963E
LSB Resolution (uV)	150	190	89

[1] Infineon-INF1197_ART_BMS_Whitepaper_d08-Whitepaper-v01_00-EN.pdf
 [2] A new battery management system could boost EV range by 20 percent | Ars Technica

BMS & BMS-ATE requirements for EV battery Cell Balancing

- Series connected cells have different SoC due to differences in manufacturing, ageing and operational conditions
 - Over-charging and deep-discharging battery cells may lead to safety hazards
- Hence, BMS balance the series State-of-Charge (SoC)
 - Current method : Passive balancing: Shunt resistor to dissipate extra charge.
 - Low complexity, but generates heat and has low power efficiency
 - Next generation: Active cell-balancing: DC-to-DC converters which redistribute charge
- BMS-ATE requirements: (1) Measure internal / external discharge FETs, (2) Emulate small-signal battery cell characteristics



Challenges of BMS-ATE

Example BMS Application Circuit:
Analog Devices ADBMS6830 16-Channel Multicell Battery Monitor

- Series stack of 4 battery modules
- 1 BMS IC per battery module





Figure 1. Typical Application Circuit

Zoom-in on one BMS-DUT



ATE hardware emulates Battery Cells

BMS-ATE needs to be high-precision, low-noise and highly-linear to accurately test BMS features:

BMS features ATE needs to test:	Required ATE-HW-features to implement test:
300uV or more accurate Analog-Front-End (AFE) and ADCs for battery Cell-voltage measurement	30-300uV accurate voltage sources
1uA or more accurate input-current	300nA – 1uA accurate current measurement capabilities
Battery temperature-sensing	Accurate I/V source and measurement capability

Additional challenges of BMS-ATE:

1. Need high channel-density, while testing 16 or higher cells
2. Series battery stack connection needs BMS to source high common-mode voltages

Overview


- Battery pack and Battery Management Systems (BMS): Critical component of EV
- BMS and BMS-ATE: Key functions and challenges
- **Proposed BMS-ATE Solution**
 - System architecture and modes of operation
 - Parametric Measurement Unit (PMU) based architecture
 - PMU measured results
- Future trends
- Conclusion



Automated Test Equipment (ATE) for EV Battery Management Systems (BMS): Challenges and Solutions



Proposed system solution for BMS-ATE: Reconfigurable stack of PMU



- System architecture based on **Parametric Measurement Unit (PMU)**
- Floating PMUs, $PMU_{16} - PMU_1$, emulate EV battery module series-connected cells
- Thanks to PMU floating-ground, hardware is configurable to two modes via switches:

— Mode 1: PMUs connected in series emulating EV battery module

- - - Mode 2: PMUs individually connected to high-voltage common-mode power supplies, $CM_{16} - CM_1$, for testing DUT maximum ratings


(Note: Figure shows a simplified system architecture for 16-series-cell BMS ATE)



Automated Test Equipment (ATE) for EV Battery Management Systems (BMS): Challenges and Solutions



BMS-ATE test (1): Measure Cell-Voltage ADC and Leakage




- DUT Specifications under test:
 - $CV_{16} - CV_1$: BMS channel Cell voltage Measurement LSB Resolution (μV)
 - $I_{LEAK_{16}} - I_{LEAK_1}$: BMS channel Input Leakage (nA)

- Typical DUT Specification Value:

Parameter	BMS IC		
	ADI ADBMS6830B	TI BQ79616	ST L9963E
Cell Voltage Measurement LSB Resolution (μV)	150	190	89
Input Leakage (nA)	250	100	300


- ATE Test Method: ATE emulates battery cells
 - Test program sets DAC input digital code, e.g., 20-bit 0x87AF4
 - PMU outputs set voltage to DUT VC terminal, e.g., 3.89765V
 - Test program records:
 - ADC cell-voltage measured by DUT
 - ADC leakage current measured by PMU

BMS-ATE test (1): Measured Elevate PMU Precision Force-Voltage



- PMU-Based ATE configuration:
 - PMU configured to drive BMS DUT with operational battery cell voltage, e.g., 3V to 5V
 - Accuracy of Forced-Voltage is within 500uV to 700uV (Can be further improved by system calibration)
- Applications:
 - Measure BMS-DUT cell-voltage resolution for state-of-charge determination

BMS-ATE test (1): Measured Elevate PMU ultra-low leakage current



- DUT Specification-under-Test:
 - Input Leakage Current

Parameter	BMS IC		
	[4] ADBMS6830B	[5] BQ79616	[6] L9963E
Input Leakage (nA)	250	100	300

- PMU-Based ATE configuration:
 - PMU can be configured to drive BMS DUT with operational battery cell voltage, e.g., 3V to 5V
 - PMU leakage current is within +/-2nA, indicating accurate measurement of DUT leakage current

BMS-ATE test (2): Measure cell balancing FET On-Resistance (Ron)



- DUT Specifications under test:
 - R_{ON}: BMS charge balancing On Resistance (Ω)

- Typical DUT Specification Value:

Parameter	BMS IC		
	[4] ADBMS6830B	[5] BQ79616	[6] L9963E
Maximum Charge Balancing FET On Resistance (Ω)	4	4.6	1.5

- ATE Test Method: ATE emulates battery cells
 - Test program sets DAC input digital code
 - PMU outputs set current, I_{FORCE} to DUT charge-balance terminal, e.g., 100mA
 - Test program records measurements :
 - PMU ADC voltage across charge-balance FET
 - Test program calculates:


$$R_{ON} = V_{ADC} / I_{FORCE}$$



Automated Test Equipment (ATE) for EV Battery Management Systems (BMS): Challenges and Solutions




BMS-ATE test (2): Measured Elevate PMU Highly Linear 1Ampere Force-Current



- PMU-Based ATE configuration:
 - Large-signal current as high as +/- 1A can be forced into DUT from ATE
 - Accuracy is within 0.1%, or +/- 1mA
 - Note: Part supports ganging of several PMUs in parallel to source higher current into the DUT
- Applications:
 - Accurate measurements of BMS charge-balance FET on-resistance with run-time-level 1 Ampere current

BMS-ATE test (3): Test DUT Maximum Rating




- DUT Specifications under test:
 - $V_{MAX16} - V_{MAX1}$: BMS maximum rated voltage
 - $I_{MAX16} - I_{MAX1}$: BMS current at maximum rated voltage

- Typical DUT Specification Value:

Parameter	BMS IC		
	ADI ADBMS6830B	TI BQ79616	ST L9963E
Maximum Rated Voltage (V)	-0.3V to 85V	-0.3V to 100V	-0.3V to 72V


- ATE Test Method: ATE emulates battery cells
 - Test program configures PMU to be connected in series with common-mode supply
 - Test program sets output voltage per maximum DUT specification
 - Test program measures DUT current and checks compliance vs. specification

Measured Elevate PMU: Ultra-Low Micro-Ampere force-current



- PMU-Based ATE configuration:
 - Small-signal current as low as +/- 2uA can be forced into DUT from ATE
 - Accuracy is within 0.05%, or +/- 1nA
- Applications:
 - Small-signal current-mode testing of the BMS-DUT

Elevate PMU ASIC High-Level Architecture



- Integrated DACs drive BMS-DUT Cell-Voltage and Charge-Balance and Bus-Bar terminals
- Multi-mode operation:
 - Force-voltage
 - Force-current
 - Measure-voltage
 - Measure-current
- High-dynamic range from micro-Ampere to Ampere, with 0.1% precision
- Test BMS-DUT Cell-Voltage resolution, input-current, balance-FET and other capabilities
- Integrated clamps with alarms for fault detection:
 - Temperature
 - Over-voltage
 - Over-current
 - Kelvin fault detection



Automated Test Equipment (ATE) for EV Battery Management Systems (BMS): Challenges and Solutions



Overview

- Battery pack and Battery Management Systems (BMS): Critical component of EV
- BMS and BMS-ATE: Key functions and challenges
- Proposed BMS-ATE Solution
 - System architecture and modes of operation
 - Parametric Measurement Unit (PMU) based architecture
 - PMU measured results
- Future trends
- Conclusion



Automated Test Equipment (ATE) for EV Battery Management Systems (BMS): Challenges and Solutions



BMS Future Trends

- Increased EV Range which needs higher-voltage battery-packs, higher precision, active cell management and active cell balance
- EV Battery aging, state-of-charge and state-of-health tracking via electrochemical impedance spectroscopy
- EV cell-to-pack or module-free design
- ElevATE PMU roadmap intercepts these trends with 120V PMU, high-resolution DACs and small-signal analog-front-end under feasibility evaluation



Automated Test Equipment (ATE) for EV Battery Management Systems (BMS): Challenges and Solutions



Overview

- Battery pack and Battery Management Systems (BMS): Critical component of EV
- BMS and BMS-ATE: Key functions and challenges
- Proposed BMS-ATE Solution
 - System architecture and modes of operation
 - Parametric Measurement Unit (PMU) based architecture
 - PMU measured results
- Future trends
- **Conclusion**



Automated Test Equipment (ATE) for EV Battery Management Systems (BMS): Challenges and Solutions



Conclusion

- EVs have proliferated the commercial mass-market
 - Continue to experience exponential growth
- BMS are key driver of EV safety, reliability and range
- Both current performance and future-trend of BMS critically depends on ATE
 - BMS is only as good as it is **designed tested by ATE**
 - Yet, BMS-ATE has many challenges
- ElevATE System and PMU-IC solution to BMS-ATE challenges has been presented
 - Configurable and scalable across battery-architecture, EV design, and future-trends



Automated Test Equipment (ATE) for EV Battery Management Systems (BMS): Challenges and Solutions



Presentation / Copyright Notice

- The presentations in this publication comprise the pre-workshop Proceedings of the TestConX Korea workshop. They reflect the authors' opinions and are reproduced here as they are planned to be presented at TestConX Korea. Updates from this version of the papers may occur in the version that is actually presented at TestConX Korea. The inclusion of the papers in this publication does not constitute an endorsement by TestConX or the sponsors.
- There is NO copyright protection claimed by this publication. However, each presentation is the work of the authors and their respective companies: as such, it is strongly encouraged that any use reflect proper acknowledgement to the appropriate source. Any questions regarding the use of any materials presented should be directed to the author/s or their companies.
- The TestConX logo, 'TestConX', and 'TestConX Korea' are trademarks of TestConX.